
Instruction Manual

Low-power battery version presence sensor



ZSS-HP05-A-MS-EB21

- QR 코드를 스캔하면 한국어 설명서, 설치 동영상, 기능 가이드 등 볼 수 있습니다.
- QRコードを読み取ると、日本語の説明書、インストールビデオ、機能ガイドが表示されます。
- من فضلك قم بمسح رمز الاستجابة السريعة(QR code)للحصول على دليل المستخدم باللغة العربية وأفلام التثبيت وصف توظائف

请扫描二维码获取中文的说明书、安装视频及功能介绍

Warnings

1.Do not disassemble, reassemble, modify or attempt to repair this product by yourself. This work should be performed by authorized professionals.
2.Product batteries should be recycled and must be recycled or disposed of separately from household waste.Dispose of batteries according to local environmental regulations.

Product description


The PIR Motion +Human presence sensor is a low-power infrared sensor that can detect the movement of people in the environment, thereby realizing security monitoring of monitored objects. At the same time,alarm information can be uploaded through the Zigbee protocol in wireless IoT mode to achieve alarm record upload.It can also be moved, placed or pasted and installed at will. Other smart hardware products can be controlled through linkage with gateway devices, and smart lights, sockets, smart curtains and other equipment can be flexibly controlled.

Product parameter

Model	ZG－204ZM
Battery Type	LR03 AAA X2 (Batteries are not given away)
Operating Voltage	DC 3V
Quiescent Current	<65uA
Illuminance Range	0~3000Lux
Communication	Zigbee3.0
Operating Temp-erature&Humidity	-10℃-55℃<95% RH
Frequency Band	2405~2480GHz
Maximum Radio Transmit Power	<+10dBm
Radar Frequency:	24GHZ


Operating instructions

1.Installing the battery
Pull down the bracket, open the back cover, and install 2 AAA batteries



Please pay special attention! The positive and negative poles of the battery are in the correct direction!
After installing the battery, snap the back cover of the bracket into the main body and push it upwards to secure the back cover.


3.Installation instructions
You can use the matching double-sided adhesive to fix the device to the wall, or use screws to fix it to the wall



Double-sided

Attention! Please do not aim the device at objects with high air flow or moving motion to avoid false alarms.
Please face the radar to the area that needs to be detected

Product description



Preparation for use

1.Download MOES App on App store or scan the QR code

Google Play
Download on the App Store

MOES App is upgraded as much more compatibility than Tuya Smart/Smart Life App,functional well for scene controlled by Siri,widget and scene recommendations as the fully new customized service.
(Note: Tuya Smart/Smart Life App still works,but MOES App is highly recommended)

2.Registration or Log in



- Download "MOES" Application.
- Enter the Register/Login interface; tap "Register" to create an account by entering your phone number to get verification code and "Set password". Choose "Log in" if you already have a MOES account.

Add device

1.This device must work with a Zigbee gateway.please add the gateway to the MOES App first.
2.Long press and hold the SET button for 3 seconds, the indicator light quickly flashes, and the device has entered the configuration network mode.
3.Wait 10~120 seconds. After adding the device successfully, Click"Done"to enter the device page to enjoy your smart life with home automation.



Declaration of conformity

Hereby,WENZHOU NOVA NEW ENERGY CO.,LTD declares that the radio equipment type ZG-204ZM is in compliance with Directive 2014/53/EU, 2014/30/EU, 2011/65/EU. The full text of the EU declaration of conformity is available at the following internet address: https://www.moestech.com/blogs/news/zss-p02-pir1-a

Troubleshooting

If you have problems installing or operating your device, please review its product data sheet: https://www.moestech.com/blogs/news/zss-hp05-a

WARRANTY INSTRUCTIONS

Dear Sir or Madam, thank you for purchasing the product.
We hope you'll enjoy using it.
The warranty for the products in the warranty card is hereby granted as follows.
As a condition of using the warranty, you must comply with the following terms and procedures:
1. Products are covered by a 24-month warranty, effective from the date of purchase of the covered product by a retail customer.
2. In order to exercise warranty rights, the purchaser must present: a) Warranty card, b) Proof of purchase (VAT invoice, financial receipt or other document confirming the actual date of purchase), unless the purchase date of the product comes from the warranty card.
3. If product quality problems occur within 24 months from the date of receipt, please prepare the product and packaging and go to the place or store where you purchased it to apply for after-sales maintenance. If the product is damaged due to personal reasons, a certain maintenance fee will be charged.

themselves.
8. If defects occur due to natural wear and tear during use, the warranty does not cover it.
9. The warranty does not cover:
a) Mechanical damage caused by the user's fault and product defects caused by such damage.
b) Damage caused by improper use of the product.
10. The rights under the guarantee will expire in the following circumstances:
a) Remove the warranty seal from the product.
b) Remove the serial number from the product.
c) Take action to eliminate physical defects in the product outside of authorized service.
d) Use non-original parts and consumables.

RECYCLING INFORMATION

All products marked with the symbol for separate collection of waste electrical and electronic equipment (WEEE Directive 2012/19 / EU) must be disposed of separately from unsorted municipal waste. To protect your health and the environment, this equipment must be disposed of at designated collection points for electrical and electronicequipment designated by the government or local authorities. Correct disposal and recycling will help prevent potential negative consequences for the environment and human health. To find out where these collection points are and how they work, contact the installer or your local authority.



FR Cet appareil, ses accessoires, se recyclent À DÉPOSER EN MAGASIN OU À DÉPOSER EN DÉCHETERIE

WARRANTY CARD

Product Information
Product Name_____
Product Type_____
Purchase date_____
Warranty Period_____
Dealer Information_____
Customer's Name_____
Customer Phone_____
Customer Address_____

Maintenance Records

Failure date	Cause Of Issue	Fault Content	Principal

Thank you for your support and purchase at we Moes, we are always here for your complete satisfaction, just feel free to share your great shopping experience with us.

★ ★ ★ ★ ★

If you have any other need, please do not hesitate to contact us first, we will try to meet your demand.

FOLLOW US

@moessmart @moes_smart MOES.Official
@moes_smart @moes_smart www.moes.net

CE RECY
AMZLAB GmbH
Lauberhof 23, ESSEN 45326
Email: info@amz-lab.de
Tel: +4917452980666
Made In China

UK RECY
EVATOST CONSULTING LTD
Address: Suite 11, First Floor, Moy Road Business Centre, Taffs Well, Cardiff, Wales, CF15 7QR
Tel: +442392180945
Email: contact@evatmaster.com

Manufacturer:
WENZHOU NOVA NEW ENERGY CO.,LTD
Address: Power Science and Technology Innovation Center, NO.238, Wei 11 Road, Yueqing Economic Development Zone, Yueqing, Zhejiang, China
Tel: +86-577-57186815
After-sale Service:service@moeshouse.com

Installationshandbuch (Deutsch)

Gerät hinzufügen

1.Dieses Gerät muss mit einem Zigbee-Gateway arbeiten, fügen Sie bitte das Gateway zur MOES-App hinzu.
2.Lange drücken und halten Sie die Taste SET für 3 Sekunden, das Anzeigelicht blinkt schnell und das Gerät ist in den Konfigurationsnetzmodus eingetreten.
3. Warten Sie 10~120 Sekunden. Nachdem Sie das Gerät erfolgreich hinzugefügt haben, klicken Sie auf "Fertig", um die Geräteseite einzugeben ihr intelligentes Leben mit Heimautomatik genießen.



Manual de instalación (Español)

Añadir dispositivos


1. Este dispositivo debe usarse con la pasarela zigbee, primero agregue la pasarela a la aplicación moes.
2. Presione el botón set durante 3 segundos, el indicador parpadea rápidamente y el dispositivo ha entrado en el modo de red de configuración.
3. Espere 10 ~ 120 segundos. Después de agregar con éxito el dispositivo, haga clic en "completar" para ingresar a la página del dispositivo. Disfrute de su vida inteligente a través de la automatización del hogar.



Manuel d'installation (Français)

Ajouter un appareil

1. Cet appareil doit fonctionner avec la passerelle ZigBee, veuillez d'abord ajouter la passerelle à l'application moes.
2. Appuyez longuement sur le bouton set pendant 3 secondes, le voyant clignote rapidement et l'appareil est entré en mode réseau configuré.
3. Attendez 10 ~ 120 secondes. Une fois que vous avez ajouté votre appareil avec succès, appuyez sur Terminer pour accéder à la page de l'appareil. Profitez de votre vie intelligente avec la domotique.



Manuale di installazione (Italiano)

Aggiungi dispositivo

1.Questo dispositivo deve funzionare con un gateway Zigbee aggiungere il gateway all'app MOES.
2.Long premere e tenere premuto il pulsante SET per 3 secondi, la luce indicatore lampeggia rapidamente e il dispositivo è entrato nella modalità di rete di configurazione.
3.Aspetta 10~120 secondi. Dopo aver aggiunto il dispositivo con successo, Fare clic su "Finito" per entrare nella pagina del dispositivo per godersi la tua vita intelligente con la domotica.



Manual de instruções (Português)

Adicionar dispositivo

1.Este dispositivo deve funcionar com um gateway Zigbee por favor adicione o gateway para o MOES App first.
2.Pressione e segure o botão SET por 3 segundos, a luz indicadora pisca rapidamente e o dispositivo entrou no modo de rede de configuração.
3.Aguarde 10~120 segundos. Depois de adicionar o dispositivo com sucesso, clique em "Concluído" para entrar na página do dispositivo para desfrutar de sua vida inteligente com automação residencial



Руководство по эксплуатации (Русский язык)

Добавить устройство

1.Это устройство должно работать с шлюзом Zigbee, сначала добавьте шлюз в приложение MOES.
2.Длительное нажатие кнопки SET в течение 3 секунд, индикатор быстро мигает, устройство вошло в режим конфигурации сети.
3.Подождите 10~120 секунд. После успешного добавления устройства, Нажмите «Готово», чтобы войти на страницу устройства Наслаждайтесь умной жизнью с помощью домашней автоматики.



Instrukcja obsługi (Polski)

Dodaj urządzenie

1.To urządzenie musi pracować z bramą Zigbee proszę dodać bramę do aplikacji MOES pnt.
2. Długo naciśnij i przytrzymaj przycisk SET przez 3 sekundy, światło wskaźnika szybko miga, a urządzenie weszło do trybu sieci konfiguracji.
3. Poczekaj 10~120 sekund. Po pomyślnym dodaniu urządzenia kliknij "Gotowe", aby wejść na stronę urządzenia Cieszyć się inteligentnym życiem dzięki automatyce domowej.



4. We recommend that you properly protect the goods when delivering them to the guarantor – for this purpose, we recommend that you use the original packaging with padding to ensure safe transportation. If you choose to use replacement packaging, we recommend that you ensure that the product is adequately protected from damage during shipping. We recommend that you place an appropriate sticker on your packaging indicating the product's susceptibility to impact, such as "Warning Glass".
5. Reported defects covered by the warranty will be considered immediately and no later than 14 days from the date of delivery of the goods to the Guarantor.
6. After checking and determining the legality of the warranty claim, the Guarantor's services will repair the product within a reasonable time, not exceeding 30 days from the date of delivery of the goods to the Guarantor. However, if hard-to-find spare parts are required, this deadline may extend the time it takes to deliver the part from the manufacturer's factory.
7. The warranty does not include the performance of maintenance and similar actions specified in the user manual, and users are obliged to do it